

FAST FIBER OPTIC 1x32 SWITCH

OVERVIEW

The SW fiber optic switch is a very fast opto-mechanical switch based on the MEMS technology. The component makes an optical connection between an optical port and either one of 32 input or output lines. The highly reliable switching mechanism use integrated micromirrors and features below 1 ms switching time and below 2.5 dB insertion loss. The switch is powered by a 5 V supply voltage. A 5 V TTL or CMOS drive signal is used to control the switching state.

The switching mechanism offers the reliability of a solid state device; it neither wears out nor degrades over time. Even after billions of cycles the switching quality stays constant. The small package withstands rugged environments and is well suited for direct mounting on printed circuit boards.

FEATURES

- reliable
- 2.5 dB insertion loss
- 1 ms response time
- 60 dB crosstalk
- miniature size
- non-latching

APPLICATIONS

- Optical Reconfiguration
- Instrumentation
- Provisioning

ORDERING INFORMATION

SW1x32-9N (smf 28, single mode fiber) SW1x32-50N (50 um core, graded index) SW1x32-62N (62.5 um core, graded index)



Contact: Sercalo microtechnology ltd Landstrasse 151, 9494 Schaan Principality of Liechtenstein Tel. +423 237 57 97 Fax. +423 237 57 48 www.sercalo.com e-mail:info@sercalo.com



TECHNICAL SPECIFICATIONS (Single Mode Variant)						
	Unit	Min	Тур	Max		
Switch						
Wavelength Range	nm	1250		1650		
Insertion Loss	dB		1.5	2.5		
Crosstalk	dB		60	50		
Backreflection	dB		55	45		
Polarisation Dependent Loss	dB			0.25		
Repeatability ¹	dB			0.002		
Switching Time	ms		0.5	1		
Switching Voltage	V			5		
Fiber Pigtail		SMF28 or				
	μm 50/125/900					
			62/125/900			
Durability	cycles	no wear out				
Package						
Power Consumption	mW		200			
Operation Temperature	°C	0		70		
Storage Temperature	°C	-40		85		
Size (L x W x H)	mm	206 x 105 x 10				
¹ value for constant temperature and polaris	ation					



ELECTRICAL CONNECTION

Optical port selection table

1					
1	2	3	4	5	Port
0	0	0	0	5	1
0	0	0	5	0	2
0	0	0	5	5	3
0	0	0	0	0	4
5	0	5	0	5	5
5	0	5	5	0	6
5	0	5	5	5	7
5	0	5	0	0	8
0	5	5	0	5	9
0	5	5	5	0	10
0	5	5	5	5	11
0	5	5	0	0	12
5	5	0	0	5	13
5	5	0	5	0	14
5	5	0	5	5	15
5	5	0	0	0	16
5	5	5	0	0	17
5	5	5	5	5	18
5	5	5	5	0	19
5	5	5	0	5	20
0	5	0	0	0	21
0	5	0	5	5	22
0	5	0	5	0	23
0	5	0	0	5	24
5	0	0	0	0	25
5	0	0	5	5	26
5	0	0	5	0	27
5	0	0	0	5	28
$\begin{array}{c c} 0 \\ 0 \\ 0 \\ 5 \\ 5 \\ 5 \\ 5 \\ 5 \\ 5 \\ 5 \\$	a por 2 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 0 0 0 0 0 0 0 0 0 0 0 0	5	0 5 0 0 5 5 0 0 5 5 0 0 5 5 0 0 5 5 0 0 5 5 0 0 0 5 5 0 0 0 5 5 0 0 0 5 5 0 0 0 5 5 0 0 0 5 5 0 0 0 5 5 0 0 0 5 5 0 0 0 5 5 5 0 0 0 5 5 5 0 0 0 5 5 5 0 0 0 5 5 5 0 0 0 5 5 5 0 0 0 5 5 5 5 0 0 0 5 5 5 5 5 0 0 0 5 5 5 5 5 5 5 0 0 0 5	0	29
0	0	5	5	5	30
0	0	5	5	0	31
0	0	3 0 0 0 0 0 5 5 5 5 5 5 5 5 5 5 0 <td< td=""><td>0</td><td>1000 5 0 5 <</td><td>1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32</td></td<>	0	1000 5 0 5 <	1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32

0 = 0 V (TTL or CMOS level)
5 = 5 V (TTL or CMOSlevel)
x = 0 V or 5 V





